

ILLUMINATION PARTS & LAMP SPECIFICATIONS

PEM FIXTURES	C131-1	C131-3	D145	E40	E40	E40	E100	E150	E200	E200	E300	E500	E500	E600	E600	E700	E700	E800	E910	E950	E1100	E1100
	C133-1	C133-3		E41	E41	E41			E300	E300	-36					E950						-7
Type of Fixture	LV	LV			LV	JC				JC	LV		LV		LV	JC	JC					LV
Type of Lamp	AR111	MR16	PAR38*	MCL	MR16	Bi-Pin	A21*	PAR38	MCL	Bi-Pin	AR111	PAR56	PAR56	PAR56	PAR56	MCL	Bi-Pin	MCL	A21*	MCL	PAR64	MR16
Lamp Connection Screws	3 x 5.3	E26/27	E11	G5.3	Bi-Pin	E26/27	E26/27	E11	G6.35	Screws	GX16d	Screws	GX16D	Screws	E11	G6.35	E11	E26/27	E11	GX16d	G5.3	-
240V, max. Watts	-	-	150	250	-	-	100	150	500	-	-	500	-	500	-	250	-	500	116	250	1000	-
120V, max. Watts	-	-	250	250	-	-	116	250	500	-	-	500	-	500	-	250	-	500	100	250	1000	-
24V, max. Watts	-	-	120	-	-	150	100	150	-	150	-	-	250		250	-	150	-	100	-	-	-
12V, max. Watts	100	3 x 65	100	-	100	100	60	100	-	100	100	-	240	-	240	-	100	-	100	-	-	7 x 65
<b>FIXTURE ROCKGUARDS</b>																						
Rockguard #10-2/-6/-7	X	X	-	-	-	-	-	X	X	X	X	-	-	-	-	-	X	X	-	-	-	-
Rockguard #10-3/-8/-9	-	-	-	-	-	-	-	-	-	-	-	X	X	X	X	-	-	-	X	-	X	X
Rockguard #10-4	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	X	X	-	X	-	-
<b>FIXTURE PARTS</b>																						
Facering Bolts (Set)	-11	-11	-11	-11	-11	-11	-11	-11	-11	-11	-11	-11	-11	-11	-11	-11	-11	-11	-11	-11	-11	-11
Lamp Connector(s)	-12	-12	-12	-12	-12	-12	-12	-12	-12	-12	-12	-12	-12	-12	-12	-12	-12	-12	-12	-12	-12	-12
Lens Gasket	-13	-13	-	-13	-12	-13	-13	-13	-13	-13	-13	-13	-13	-13	-13	-13	-13	-13	-13	-13	-13	-13
Clear Convex Lens	-14	-14	-	-14	-14	-14	-14	-14	-14	-14	-14	-14	-14	-14	-14	-14	-14	-14	-14	-14	-14	-14
Color Lens (Color ?)	-15	-15	-	-15	-15	-15	-15	-	-15	-15	-15	-15	-15	-15	-15	-15	-15	-15	-15	-15	-15	-15
Cordseal Gland	-17	-17	-17	-17	-17	-17	-17	-17	-17	-17	-17	-17	-17	-17	-17	-17	-17	-17	-17	-17	-17	-17
Cordseal Washer	-18	-18	-18	-18	-18	-18	-18	-18	-18	-18	-18	-18	-18	-18	-18	-18	-18	-18	-18	-18	-18	-18
Cordseal Plug	-19	-19	-19	-19	-19	-19	-19	-19	-19	-19	-19	-19	-19	-19	-19	-19	-19	-19	-19	-19	-19	-18
Body 'O' Ring Seal	-	-	-31	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
Base 'O' Ring Seal	-	-	-	-32	-32	-32	-	-	-	-	-	-	-	-32	-32	-32	-	-	-	-	-	-
Facering 'O' Ring Seal	-	-	-33	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-
St. St. Reflector -	-	-	-	-	-	-	-	-	-37	-37	-	-	-	-	-	-	-37	-37	-	-	-	-
Lampholder Mount / Clamp	-	38CL	38PL	-	-	38LV	-38JC	-	-	-	-38JC	38CL	-	-	-38	-38JC	-	-38	-38	-	-	-38
St. St. Wiring Cover	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-39	-39	-	-	-	-
* = Verify lamp size (M.O.L.) to fit lightfixture																						

**JUNCTION, DECK BOXES, MULTIPLE CABLE ENTRIES & CORDSEALS**

Cover Gasket or 'O' Ring Seal = State Catalog Number + -21

Base Plate 'O' Ring seal for J36 = J36-22 / Valve 'O' Ring Seal for J36 = J36-23

Set of Cover Bolts = State Catalog Number + -25 / Ground (Earth) Screw Assembly (1 only) = State Catalog Number + -28

**CORDSEALS & SINGLE CABLE ENTRIES**

Gland = State Catalog Number + - 03

Compression Washer = State Catalog Number + -04 / Compression Nut = State Catalog Number + -05